

Grandstream Networks, Inc.

Remote Control Upgrading Instructions

Table of Content

Document Purpose
Prerequisite
Upgrade Remote Control
Install Remote Control App
Upgrade Remote Control
Reboot Device

Document Purpose

This document describes the detailed steps to upgrade the GVC320x's remote control software version. Upgrading remote control makes sure the remote control has the latest software which contains new fixes. For issues such as touchpad on remote control is not working, please follow below operations to upgrade and restore it.

Prerequisite

- Please make sure GVC320x is using the latest official or Beta firmware in Grandstream website:

http://www.grandstream.com/support/firmware

- Please make sure your remote control is paired with GVC320x device.
- It is recommended to replace a new battery on your remote control to ensure sufficient battery supply for upgrading process.

Upgrade Remote Control

Install Remote Control App

Step 1: On your PC, download remote control firmware from the following link:

http://www.grandstream.com/sites/default/files/Resources/GVC320x_RemoteControl_Firmwar e.zip

Step 2: Unzip the package. Open the folder and find file "upgrade_rmt.apk". Copy file "upgrade_rmt.apk" to a USB flash drive plugged in the PC.

Step 3: Plug in USB flash drive into GVC320x USB port.

Step 4: On GVC320x, go to File Manager -> USB Disk, click on "upgrade_rmt.apk" to install it.





Step 5: If you see "Install blocked" prompt, please go to Menu->Settings->System-> Security, enable "Unknown Sources" option.

192.168.129.83 🕓 Acc	count (no	ot configured)			09:26 🖬 🖬
📄 File Manage					
/USB Disk1/		RemoteControl			
LOST.DIR	upgrade				
	пп.арі	Install blocked			
		For security, your of block installation of from unknown sou	levice is set to f apps obtained rces.		
		Cancel	Settings		
192.168.129.83 Acc	count (no	ot configured)			🖃 🛡 📾 🖺 🗘 09:26
Ø System					
Language & inp	Screer	1 lock			
Date & time			6		
Power manager	Device	Your device and pe	s Irsonal data are		
Site name	Devic View or	more vulnerable to apps from unknow	be attacked by n sources. You		
Storage	Unkno	for any damage to	your device or		
Apps		loss of data that m	ay result from		
Accounts	Verify Disallov	Cancel	ОК	cause harm	
Web access					
Security 🕨 🕨					
	Truste Display	d Credentials trusted CA certificates			

Step 6: After allowing Unknown Sources Installation, please go back to File Manager->USB Disk, click on "upgrade_rmt.apk" to install it.

192.168.129.83 🖎 Acco	ount (not configur	red)			09:38 🛱 🛱
📄 File Manager	🖌 🖉 Remot	eControl	loto — Edit .		
/USB Disk1/	Do you want to	Do you want to install this application? It will get access			
	to:				
	the modify or	delete the conte	nts of your SD card		
LOST.DIR	mt.apl	contents of your S	SD card		
	Can	cel	Install		
			inotan		
100 100 100 00	. /				
192.168.129.83 🖎 Acco	ount (not configur	red)			1 🔒 📓 🗘 09:27
RemoteControl	ount (not configur	red)			🛱 📓 🗘 09:27
App installed.	bunt (not configur	red)			● 🛱 🛱 🗘 09:27
App installed.	ount (not configur	'ed)			0 🖬 🖩 ⊖ 09:27
App installed.	ount (not configur	red)			0 🖬 🗎 ⊖ 09:27
App installed.	ount (not configur	red)			0 🖬 🗎 ⊖ 09:27
App installed.	ount (not configur	red)			0 🖬 🖩 ⊖ 09:27
App installed.	ount (not configur	red)			0 🖬 🗎 ⊖ 09:27
App installed.	ount (not configur	red)			0 🖬 🗎 ⊖ 09:27
App installed.	ount (not configur	red)			●
App installed.	ount (not configur	red)			●
RemoteControl App installed.	ount (not configur	-ed)			●
App installed.	ount (not configur	red)			0

Upgrade Remote Control

Step 1: Click on "Open" or go to GVC320x LCD -> Applications to open "Remote Control" app. Step 2: Click on "Upgrade" -> Press "OK" to start upgrade process.

192.168.129.83 Account (n	ot configured) nware upgrade		🖬 🖱 🔒 🛱 🗘 09:31
MAC address Connection status: Remote control version:	Remote control firm	nware upgrade	۔ Disconnected 1.0.1.1
Upgrade version:	Please ensure that enough power, plea program upgrades power supply in the upgrading. The net temporarily turned	the remote has ase don't interrupt or cut off remote e process of work will be off.	1.0.1.2
	ОК	Cancel	

Step 3: The upgrade process will take about 2 minutes, please wait for the app to quit automatically. This means upgrading is completed.

Note: If there is a prompt "Found new firmware for remote control" displayed after upgrading, please click "Cancel". This is to keep the remote control stay on the just upgraded software version.

192.168.129.83 Account (n	ot configured)		0 🛍 📓 🗘 16:13
Applications			
RemoteCont rol Speedte	Found new firmwar control Do you want to up version?	e for remote grade to new	
	Cancel	ОК	

Reboot Device

On GVC320x, go to Settings -> Maintenance -> Reboot to reboot the device. Your remote control will be successfully recovered after reboot.

192.168.129.83 🕓 Accour	nt (not configured)		🖬 🖱 🛱 🖀 🗘 09:31
🔅 Settings			
	stere	\	
(📥)	₹9 7		
	AL.	0 v	
Accounts	System	Maintenance	Network
~1 \\			\bigcirc
「 」 「 」 " 」		Y 🏚	
Audio	Video	Poriphoral	Status
Audio	viueo	renpheral	Status
		이 가지 않는 것을 하는 것이 있는 것이 같이 있는 것이 없는 것이 없 않 않이 않	an an the section of
102 168 120 83 🔊 Accourt	nt (not configured)		□ ■ 品 図 ○ 00:31
192.168.129.83 🕥 Accour	nt (not configured)		🗳 🖶 🖨 📓 🗘 09:31
192.168.129.83 (a) Accour	nt (not configured)		🗳 🖶 🖨 📓 🗘 09:31
192.168.129.83 (a) Accourt Maintenance Upgrade	nt (not configured)		🗳 🖶 🛱 🛱 🗘 09:31
192.168.129.83 (a) Accourt Maintenance Upgrade Troubleshootinc	nt (not configured)		🗉 🛢 🔒 🗟 🔿 09:31
192.168.129.83 (a) Account Maintenance Upgrade Troubleshooting Factory reset	nt (not configured)		🖬 🖱 🖨 📓 🗘 09:31
192.168.129.83 (a) Account Maintenance Upgrade Troubleshooting Factory reset	nt (not configured) Reboot		🗳 🖶 🖻 🖺 🔿 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re	boot your device?	🖬 🖶 🛱 🛱 🗘 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re	boot your device?	🗳 🖶 🖻 🖺 🔿 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re	boot your device?	k # 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re Cancel	boot your device?	🖶 🖶 🗟 🗘 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re Cancel	boot your device?	🖶 🖨 🖺 🗘 09:31
192.168.129.83 Account Maintenance Upgrade Troubleshootinc Factory reset Reboot	nt (not configured) Reboot Do you want to re Cancel	boot your device?	u 🖶 🖻 🖺
192.168.129.83 Account Maintenance Upgrade Troubleshooting Factory reset Reboot	nt (not configured) Reboot Do you want to re Cancel	boot your device?	n
192.168.129.83 Account Maintenance	nt (not configured) Reboot Do you want to re Cancel	boot your device?	u 🖶 🖻 🖺